

Boreal FreeJack 4" Round Flush Canopy



DESCRIPTION

Recycled sand-cast bronze metal canopy. Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformer (included) fits in junction box. One FreeJack port; for ceiling or wall.

INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). Transformer (included) fits in junction box. For ceiling or wall. If wall mounting, head should be no longer than 6".

DIMMING

120V IN/12V OUT and 120V IN/24V OUT dimmable with a standard incandescent dimmer (not included). 277V IN/12V OUT dimmable with a 277V incandescent dimmer (not included).

OTHER INFORMATION

For use with any 12 or 24 volt halogen FreeJack pendant or head (sold separately).

WEIGHT

1.06lb / 0.48kg

ORDERING INFORMATION



700FJ4RB FINISH	VOLTAGE
Z ANTIQUE BRONZE	120V IN/12V OUT
S WHITE BRONZE	024 120V IN/24V OUT
	277 277V IN/12V OUT

While we feel they look very nice together, the boreal finishes will not be an exact match to existing satin nickel and antique bronze hardware.



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
 Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700FJ4RB _____
FIXTURE TYPE: _____
JOB NAME: _____
NOTES: _____

